

DS-K1201AMF Fingerprint Reader

114-126



- A group of messy code encrypted data for the security of fingerprint storage
- Supports RS-485 communication with 19200bps-N-8-1 transmission rate. There are CRC test for the protocol
- Supports M1 card reading
- Card induction distance is 30 mm to 100 mm
- Supports multiple authentication modes (card, fingerprint, and card + fingerprint)
- Optical CMOS fingerprint module. The characters of fingerprint can be export to the card reader
- Max. 5000 fingerprints storage
- Adopts the optical fingerprint module, supporting 1:N mode (fingerprint, card + fingerprint) and 1:1 mode (card + fingerprint)
- Fingerprint comparison time: $1:1 \leq 1\text{ s}$, $1:1000 \leq 1\text{ s}$; $\text{FRR} \leq 0.01\%$, $\text{FAR} \leq 0.001\%$
- Communication circuit is designed with optical coupling isolation and noise suppression function
- Built-in buzzer for status indication
- Accurate data and time display provided by built-in electronic clock and watchdog program to ensure the basic function of the terminal
- Tamper-proof function

▪ Specification

Interface	
TAMPER	1
Authentication	
Fingerprint module	Optical fingerprint module
Fingerprint comparing mode	1:1/1:N
Card type	M1 card
General	
Power supply	12 VDC $\pm$ 10%
Power consumption	$\leq$ 1.6 W
Working temperature	-40 °C to 70 °C (-40 °F to 158 °F)
Working humidity	10% to 90% (no condensing)
Dimensions	62 mm $\times$ 132 mm $\times$ 44 mm (2.44" $\times$ 5.20" $\times$ 1.73")
Installation	Surface mounting
Buzzer	Support

▪ Available Model

DS-K1201AMF



Innovative Electronic Solutions
www.ness.com.au



NSW Ph 02 8825 9222
sales@ness.com.au

VIC Ph 03 9875 6400
nessmelb@ness.com.au

QLD Ph 07 3399 4910
nessbris@ness.com.au

WA Ph 08 9328 2511
nessper@ness.com.au

SA Ph 08 8152 0000
adelaide@ness.com.au