

Setup Guide for:

114-452 Hikvision DS-K1T502DBWX-C Access Control Terminal

How to add 114-452 DS-K1T502DBWX-C Access Terminal to a Hikvision NVR

Purpose


Live view or record video from 114-452 DS-K1T502DBWX-C on a Hikvision NVR.

Device List

114-452 DS-K1T502DBWX-C V1.7.1 220719

Any Hikvision NVR running V4.0 and later firmware.

1. Login to the NVR web configuration page, and go to Configuration-> Camera Management-> IP Camera-> Custom Protocol, Single Click



2. Input the custom protocol name and corresponding information as below in the pop up menu:

Custom Protocol

Custom Protocol 1

*Protocol Name: HIKVISION_RTSP

HIKVISION DAHUA UNVIEW
TPLINK HUAWAI

Main Stream

Enable Stream:

Protocol: RTSP

Transfer Protocol: Auto

*Port: 554

Stream Path: ch1/main/av_stream

RTSP Example: [Type]/[IP Address]:[Port]/[Path]
rtsp://192.168.0.1:554/ch1/main/av_stream

OK Cancel

Custom Protocol

Custom Protocol 1

*Protocol Name: HIKVISION_RTSP

HIKVISION DAHUA UNVIEW
TPLINK HUAWAI

Sub-Stream

Enable Stream:

Protocol: RTSP

Transfer Protocol: Auto

*Port: 554

Stream Path: ch1/sub/av_stream

RTSP Example: [Type]/[IP Address]:[Port]/[Path]
rtsp://192.168.0.1:554/ch1/sub/av_stream

OK Cancel

3. Back to the IP camera page, click Add and select the custom protocol HIKVISION_RTSP and input the corresponding information, click OK

HIKVISION Live View Playback file Application Configuration

Local System Settings Maintenance Security User Management Camera Management Live View Settings Audio Management Video/Audio Event Network

IP Camera More Configure

+ Add IP Camera

IP Camera

*IP Camera Address: 10.7.68.13

Protocol: HIKVISION_RTSP

Management Port: 554

*User Name: admin

Password: [masked]


Password Confirm: [masked]

Transfer Protocol: Auto

IP Camera Time Sync: Enable

OK Cancel

- When the status shows online, you can get LiveView or set recording schedule for this channel



How-To Guide
 How to add 114-452 DS-K1T502DBWX-C
 Access Terminal to a Hikvision NVR
 Tested 26/09/2022



Innovative Electronic Solutions
www.ness.com.au

National Customer Service Centre
 Ph: 1300 551 991
techsupport@ness.com.au



Sales Branches

NSW Ph 02 8825 9222 sales@ness.com.au	VIC Ph 03 9875 6400 nessmelb@ness.com.au	QLD Ph 07 3399 4910 nessbris@ness.com.au	WA Ph 08 9328 2511 nessper@ness.com.au	SA Ph 08 8152 0000 adelaide@ness.com.au
--	--	--	---	---