

MULTICOM

4G

SERIES

# MULTICOM 4G SERIES

Multi-Apartment Wireless Audio Intercom



- Calls up to 1000 families from a single SIM card.
- Visitors can scroll for residents on the digital screen or enter an apartment number to call.
- 3 dial-out numbers per apartment (3000 total).
- 1 keypad code per apartment (1000 total).
- Prox reader comes as standard, with 3 prox cards/tags per apartment (3000 total).
- Built-in time clock for auto opening and closing of gates, barriers, or doors in busy periods or for daytime operation.
- Visitor codes/cards - 250 Permanent/Time-restricted.
- Do not disturb feature.
- 2 Relays.

# Multicom Classic

M u l t i   A p a r t m e n t   I n t e r c o m



## DETAILS

Dial Out Numbers per Apartment	3 per apartment (3000 Total)	Relays	2
Keypad Codes per Apartment (6 digit)	1 per apartment (1000 Total)	Relay Type	N/C and N/O
Prox Cards/Tags per Apartment	3 per apartment (3000 Total)	Relay Load	2 amps, 24v ac max
Automatic Trigger Events per Week	10	Power Consumption	310mA on dial out, 2amp peak demand
Modem Models	4G EU, 4G USA, 4G AUS/NZ	Power Supply	24v dc (24v dc 2A adaptor included)

## VISITOR CODES/CARDS

	Permanent	Time-restricted	Temporary
Visitor Prox Cards	250	250	50
Keypad Codes (4 digits)			
Caller ID			

### Ordering Information

106-889 MULTICOM CLASSIC 4G

Datasheet Rev4 (1000 families)



Innovative Electronic Solutions  
www.ness.com.au



**NSW** Ph 02 8825 9222  
sales@ness.com.au

**VIC** Ph 03 9875 6400  
nessmelb@ness.com.au

**QLD** Ph 07 3399 4910  
nessbris@ness.com.au

**WA** Ph 08 9328 2511  
nessper@ness.com.au

**SA** Ph 08 8152 0000  
adelaide@ness.com.au