

## NESS COMBO SIREN

Attractive Rugged Combination Siren and Blue Strobe for External or Internal use. Compatible with all Ness Control Panels.

Typical wiring diagram for most Ness control panels.

\* Applying 12V to the LED terminals lights one LED in the LED array. This may be used as an indicator light driven by an automation output on the control panel.

- Housing material: UV PC / white
- IP55 Weather-resistant
- Operating voltage: 12-15VDC
- Rated current: 380mA (Alarm Mode)
- Siren 115dB @ 1m
- Strobe technology: LED
- Strobe Colour: Blue
- Tamper Switch protection Front & Rear
- Size: 210 x130 x 78mm

Part No. 100-245 Ness Combo Siren Blue



Innovative Electronic Solutions www.ness.com.au









NSW Ph 02 8825 9222 sales@ness.com.au

VIC Ph 03 9875 6400 nessmelb@ness.com.au

QLD Ph 07 3399 4910 nessbris@ness.com.au

WA Ph 08 9328 2511 nessper@ness.com.au

SA Ph 08 8152 0000 adelaide@ness.com.au