

10 Watt Audio Amplifier

ELK-800

The ELK-800 is a compact, low cost audio amplifier designed for paging (public address) applications. The ELK-800 can be centrally or remotely installed. It operates on low voltage, thus saving money by requiring only 22-24 gauge telco or alarm type wire. It can drive multiple speakers and features short circuit protection and built-in volume adjust.



101-265

FEATURES

- Small, Compact Public Address Amplifier
- Expanded Telephone System Paging
- Amplified Telephone Ringer Where Speaker Tone Signaling Is Available
- Eliminates Large Bulky Amplifiers
- No Need For 70 Volt Line Transformers
- Uses Inexpensive 22-24 AWG Wire
- Drives Ordinary Horn or Cone Speakers
- Built-in Volume Control
- Lifetime Limited Warranty

SPECIFICATIONS

- Output Rating: 10 Watts**
- Speaker (Output) Load: 2 to 16 Ohms**
- Power Input: 12 to 18 Volts AC or DC**
- Current Draw: 50 to 800 mA
- Input Impedance: 1000 Ohms nominal
- Size: 4.5" x 3" x 1.2"



Innovative Electronic Solutions
www.ness.com.au



NSW Ph 02 8825 9222
sales@ness.com.au

VIC Ph 03 9875 6400
nessmelb@ness.com.au

QLD Ph 07 3399 4910
nessbris@ness.com.au

WA Ph 08 9328 2511
nessper@ness.com.au

SA Ph 08 8152 0000
adelaide@ness.com.au